

Xunrui Shenzhen Optoelectronics Technology Co., Ltd.



(ISO9001)

CERT. No. QAC0946535 CERT. No. HKG002005 (ISO14001)

H080IWV50E3564-CT2

Product Specification

Customer:

Model Name:

Date:

Version:

Preliminary Specification



Final Specification

For Customer's Acceptance

Approved by	Comment

Approved by	Reviewed by	Prepared by



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

Table of Contents

1. Record of Revision	3
2 General Specifications	4
3 Input/Output Terminals	5
4 Absolute Maximum Ratings	8
5 Electrical Characteristics	8
6 Optical Characteristics	13
7 Environmental / Reliability Tests	16
8 Mechanical Drawing	17
9 Packing	18
10 Precautions For Use of LCD modules	19



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

1. Record of Revision

Rev	Issued Date	Description	Editor
1.0	2018/3/11	First Release.	Li Tang



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

2 General Specifications

	Feature	Spec
	Size	8 inch
	Resolution	800(horizontal)*480(Vertical)
	Interface	RGB
	Connect type	Connector
	Color Depth	16.7M
	Technology type	a-Si
Characteristics	Display Spec. Pixel pitch (mm)	0.0736(W) X 0.2070(H) mm
	Pixel Configuration	R.G.B. Vertical Stripe
	Display Mode	Normally White
	Driver IC	-
	Surface Treatment	HC
	Viewing Direction	12 O'clock
	Gray Viewing Direction	6 O'clock
	LCM (W x H x D) (mm)	204*128*8
	Active Area(mm)	176.64 x 99.36
Mechanical	With /Without TSP	With CTP
	Weight (g)	TBD
	LED Numbers	27 LEDs

Note 1: Viewing direction is follow the data which measured by optics equipment.

Note 2: Requirements on Environmental Protection: RoHS

Note 3: LCM weight tolerance: +/- 5%



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

3 Input/Output Terminals

No.	Symbol	Description
1,2	VLED+	Power for LED backlight anode
3,4	VLED-	Power for LED backlight cathode
5	GND	Ground
6	VCOM	Common voitage
7	DVDD	Ppwer for Digital Circuit
8	MODE	DE/SYNC mode select
9	DE	Data input Enable
10	VS	Vertical sync signal
11	HS	Horizontal sync Signal
12~19	B7~B0	Data bus
20~27	G7~G0	Data bus
28~35	R7~R0	Data bus
36	GND	Power ground
37	DCOLK	Sample clocd
38	GND	Power ground
39	L/R	Left/right selection
40	U/D	Up/down selection
41	VGH	Gata on voltage
42	VGL	Gata off voltage
43	AVDD	Power for analog circuit
44	RESET	Global reset pin
45	NC	NO connection
46	VCOM	Common Voltage
47	DITHB	Dither function
48	GND	Power ground
49~50	NC	NO connection

I: input, O: output, P: Power

Note 1: DE/SYNC mode select. Normally pull high.

When select DE mode, MODE=" 1" , VS and HS can pull high or be ground.

When select SYNC mode, MODE= "0", DE can pull high or be ground.

Note 2: When input 18 bits RGB data, the two low bits of R,G and B data must be grounded.

Note 3: Data shall be latched at the falling edge of DCLK.




Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

Note 4: Selection of scanning mode

tting of scar	n control input	Scanning direction			
U/D	L/R	Scanning direction			
GND	DVpp	Up to down, left to right			
DVpd	GND	Down to up, right to left			
GND	GND	Up to down, right to left			
DVDD	DVDD	Down to up, left to right			

Note 5: Definition of scanning direction. Refer to the figure as below:

Up



Note 6: Global reset pin. Active low to enter reset state. Suggest to connect with an RC reset circuit for stability. Normally pull high.

Note 7: Dithering function enable control, normally pull high.

When DITHB=" 1" ,Disable internal dithering function,

When DITHB=" 0", Enable internal dithering function,



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

4 Absolute Maximum Ratings

	(Note 1)								
Item	Cumhal	Val	ues						
	Symbol	Min.	Max.	Unit	Remark				
Power voltage	DVDD	-0.3	5.0	V					
	AV _{DD}	6.5	13.5	V					
	V _{GH}	-0.3	40.0	V					
	V _{GL}	-20.0	0.3	V					
	V _{GH} -V _{GL}	4	40.0	v					
Operation Temperature	T _{OP}	-20	70	°C					
Storage Temperature	T _{ST}	-30	80	°C					

Note 1: The absolute maximum rating values of this product are not allowed to be exceeded at any times. Should a module be used with any of the absolute maximum ratings exceeded, the characteristics of the module may not be recovered, or in an extreme case, the module may be permanently destroyed.



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

5 Electrical Characteristics

5.1 Driving TFT LCD Panel


ltem	fumbal		Values		Unit	Remark
nem	Symbol	Min.	Тур.	Max.	Unit	Remark
Power voltage	DVDD	3.0	3.3	3.6	V	Note 2
	AVDD	10.2	10.4	10.6	V	
	V _{GH}	15.3	16.0	16.7	V	
	VgL	-7.7	-7.0	-6.3	V	
Input signal voltage	V _{COM}	3.4	4.4	5.4	V	Note 4
Input logic high voltage	VIH	0.7 DV _{DD}	2 7 5	DVDD	ΥJ	
Input logic low voltage	VIL	0	-	0.3 DV _{DD}	V	Note 3

Note 1: Be sure to apply DVDD and VGL to the LCD first, and then apply VGH. Note 2: DVDD setting should match the signals output voltage (refer to Note 3) of

customer's system board.

Note 3: DCLK,HS,VS,RESET,U/D, L/R,DE,R0~R7,G0~G7,B0~B7,MODE,DITHB.


Note 4: Typ. Vcom is only a reference value, it must be optimized according to each LCM. Be sure to use VR;






Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

5.2.1 Power Sequence



 $DV_{DD} \rightarrow VGL \rightarrow VGH \rightarrow Data \rightarrow B/L$

Power off:



 $B/L \rightarrow Data \rightarrow VGH \rightarrow VGL \rightarrow DV_{DD}$



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

5.2.2 Timing Characteristics

AC Electrical Characteristics


			Values	ł		
Item	Symbol	Min.	Тур.	Max.	Unit	Remark
HS setup time	Thst	8	27	1750	ns	
HS hold time	Thhd	8			ns	
VS setup time	Tvst	8	82	1620	ns	
VS hold time	Tvhd	8	2-	12=11	ns	
Data setup time	Tdsu	8			ns	1.
Data hole time	Tdhd	8	-	1.5	ns	
DE setup time	Tesu	8	- 2	121	ns	
DE hole time	Tehd	8	14	8 - 8	ns	
DV _{DD} Power On Slew rate	TPOR		<u>.</u> -	20	ണട	From 0 to 90% DVDD
RESET pulse width	TRst	1	. .		ms	
DCLK cycle time	Tcoh	20	-		ns	
DCLK pulse duty	Towh	40	50	60	%	

5.3 Data Input Format





Xunrui Shenzhen Optoelectronics Technology Co., Ltd.



5.3 .1 Timing

ltem	Combal		Values		. .	
	Symbol	Min.	Тур.	Max.	Unit	Remark
Horizontal Display Area	thd	2	β 00	1129	DCLK	
DCLK Frequency	fclk	26.4	33.3	46.8	MHz	
One Horizontal Line	th	862	1056	1200	DCLK	
HS pulse width	thpw	1	27	40	DCLK	
HS Blanking	thb	46	46	46	DCLK	
HS Front Porch	thfp	16	210	354	DCLK	

Item	Similar		Values		Unit	Remark
ltem	Symbol	Min.	Тур.	Max.	Unit	
Vertical Display Area	tvd	276	480	070	TH	
VS period time	tv	510	525	650	TH	
VS pulse width	tvpw	1		20	тн	
VS Blanking	tvb	23	23	23	ΤН	
VS Front Porch	t∨fp	7	22	147	TH	



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

5.3 Driving Backlight

Item	Symbol	MIN	ТҮР	MAX	Unit	Remark
Forward Current	$I_{\rm F}$	-	270	-	mA	
Forward Voltage	VF	9.0	9.8	10.6	V	
Backlight Power consumption	W _{BL}	-	TBD	-	W	

Note 1: Each LED : IF =30 mA, VF =3.2V.

Note 2: Optical performance should be evaluated at Ta=25 $^\circ\!\!\mathbb{C}$ only.

Note 3: If LED is driven by high current, high ambient temperature & humidity condition. The life time of LED will be reduced. Operating life means brightness goes down to 50% initial brightness. Typical operating life time is estimated data.




Figure : LED connection of backlight



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

6 Optical Characteristics

Items		Symbol	Condition	Min.	Typ.	Max.	Unit	Remark
Viewing angles		θ∟		60	75	-		
		θ _R		60	75	-	Degree.	Note2
		θτ		40	70	-		NOLEZ
		θΒ		60	75	-		
Contract Datio		CR	Θ =0	-	400	500	-	Note1,
	Contrast Ratio							Note3
Dognongo Timo		Ton	25° C	-	10	20	ma	Note1,
Kesponse II	Response Time	TOFF	25 0	-	15	30	ms	Note4
Chromaticity Whit		Xw	Normal $\Theta = 0^{\circ}$	0.26	0.31	0.36	-	Note1,
	White	Yw		0.28	0.33	0.38	-	Note5
Color Gamut		NTSC	0 -0	-	50	-	%	Note1,
								Note6
Luminanc	e	т		300	350			Note1, Note7
		NTSC				-	%	

Test Conditions:


- 1. DvDD=3.3V,the ambient temperature is 25° C.
- 2. The test systems refer to Note 1 and Note 2.

Note 1:Definition of optical measurement system.

The optical characteristics should be measured in dark room. After 5 minutes operation, the optical properties are measured at the center point of the LCD screen. All input terminals LCD panel must be ground when measuring the center area of the panel.



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.



Note 2: Definition of viewing angle range and measurement system.

viewing angle is measured at the center point of the LCD by CONOSCOPE(ergo-80).




Fig. 1 Definition of viewing angle

Note 3: Definition of contrast ratio


Note 4: Definition of Response time

The response time is defined as the LCD optical switching time interval between "White" state and "Black" state. Rise time (TON) is the time between photo detector output intensity changed from 90% to 10%. And fall time (TOFF) is the time between photo detector output intensity changed from



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

10% to 90%.



Note 5: Definition of color chromaticity (CIE1931)

Color coordinates measured at center point of LCD.

Note 6: Definition of Luminance Uniformity

Active area is divided into 9 measuring areas (Refer Fig. 2). Every measuring point is placed at the center of each measuring area.

Luminance Uniformity(U) = Lmin/ Lmax100%

L-----Active area length W----- Active area width




Fig. 2 Definition of uniformity

Lmax: The measured maximum luminance of all measurement position.

Lmin: The measured minimum luminance of all measurement position.

Note 7: Definition of Luminance :

Measure the luminance of white state at center point.



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

7 Environmental / Reliability Tests

No	Test Item	Condition	Remarks	
1	High Temperature Opeartion	Ts=+70°C, 240hrs	Note 1 IEC60068-2-2, GB2423. 2-89	
2	Low Temperature Opeartion	Ta= -20°C, 240hrs	Note 2 IEC60068-2-1 GB2423.1-89	
3	High Temperature Storage	Ta=+80°C, 240hrs	IEC60068-2-2 GB2423. 2-89	
4	Low Temperature Storage	Ta= -30°C, 240hrs	IEC60068-2-1 GB/T2423.1-89	
5	High Temperature & Humidity Storage	Ta= +60°C, 90% RH max, 160 hours	IEC60068-2-3 GB/T2423.3-2006	
6	Thermal Shock (Non-operation)	-30°C 30 min ~ +80°C 30 min Change time: 5min, 30 Cycle	Start with cold temperature,end with high temperature IEC60068-2-14, GB2423.22-87	
7	Electro Static Discharge (Opeartion)	C=150pF, R=330 Ω , 5 points/panel Air: \pm 8KV, 5 times; Contact: \pm 4KV, 5 times; (Environment: 15°C ~ 35°C, 30% ~ 60%, 86Kpa ~ 106Kpa)	IEC61000-4-2 GB/T17626.2-1998	
8	Vibration (Non-operation)	Frequency range: 10~55Hz, Stroke: 1.mm Sweep: 10Hz~55Hz~10Hz 2 hours for each direction of X .Y. Z. (package condition)	IEC60068-2-6 GB/T2423.5-1995	
9	Shock (Non-operation)	60G 6ms, $\pm X$, $\pm Y$, $\pm Z$ 3 times for each direction	IEC60068-2-27 GB/T2423.5-1995	
10	Package Drop Test	Height: 80 cm, 1 corner, 3 edges, 6 surfaces	IEC60068-2-32 GB/T2423.8-1995	


Note: 1. T_S is the temperature of panel's surface.

2. Ta is the ambient temperature of sample.



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

8 Mechanical Drawing





Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

9 Packing

Packing Method



Xunrui Shenzhen Optoelectronics Technology Co., Ltd.

10. Precautions for Use of LCD modules

10.1 Handling Precautions

10.1.1. The display panel is made of glass. Do not subject it to a mechanical shock by dropping it from a high place, etc.

10.1.2. If the display panel is damaged and the liquid crystal substance inside it leaks out, be sure not to get any in your mouth, if the substance comes into contact with your skin or clothes, promptly wash it off using soap and water.

10.1.3. Do not apply excessive force to the display surface or the adjoining areas since this may cause the color tone to vary.

10.1.4. The polarizer covering the display surface of the LCD module is soft and easily scratched. Handle this polarizer carefully.

10.1.5. If the display surface is contaminated, breathe on the surface and gently wipe it with a soft dry cloth. If still not completely clear, moisten cloth with one of the following solvents:

- Isopropyl alcohol
- Ethyl alcohol

Solvents other than those mentioned above may damage the polarizer. Especially, do not use the following:

- Water
- Ketone
- Aromatic solvents
- 10.1.6. Do not attempt to disassemble the LCD Module.
- 10.1.7. If the logic circuit power is off, do not apply the input signals.
- 10.1.8. To prevent destruction of the elements by static electricity, be careful to maintain an optimum work environment.
- 10.1.8.1. Be sure to ground the body when handling the LCD Modules.
- 10.1.8.2. Tools required for assembly, such as soldering irons, must be properly ground.
- 10.1.8.3. To reduce the amount of static electricity generated, do not conduct assembly and other work under dry conditions.
- 10.1.8.4. The LCD Module is coated with a film to protect the display surface. Be care when peeling off this protective film since static electricity may be generated.

10.2 Storage Precautions

10.2.1. When storing the LCD modules, avoid exposure to direct sunlight or to the light of fluorescent lamps.

10.2.2. The LCD modules should be stored under the storage temperature range If the LCD modules will be stored for a long time, the recommend condition is:

Temperature : 0° C ~ 40° C Relatively humidity: $\leq 80\%$

10.2.3. The LCD modules should be stored in the room without acid, alkali and harmful gas.

10.3 Transportation Precautions

The LCD modules should be no falling and violent shocking during transportation, and also should avoid excessive press, water, damp and sunshine.